

PASSAP®**Electronic-6000
Versions****Main RAM Memory**

Years :	Serial number :	Main RAM memory :	Part number :
1988 – 1992	Up to 6 036 711	8 MB	92.904.31
1993 - 1999	From 7 037 001	32 MB	92.904.41

In order to modify the memory size of Electronic-6000 from 8 MB to 32 MB it is indispensable to change simultaneously the main printed board and the main integrated circuit (IC).

A main integrated circuit of 32 MB must never be plugged to a main printed board of 8 MB !

Program and pattern ICs

The program and pattern ICs must always be of the same version.

Program IC + Pattern IC	Main RAM Memory	Usable memory
03, 13, 23	8 MB	8 MB
03, 13, 23	32 MB	8 MB
33, 43, 53	8 MB	8 MB
33, 43, 53	32 MB	32 MB

Motor Electra 4600

Program IC + Pattern IC	Motor Electra 4600
03, 13, 23	Not controllable
33, 43, 53	Controllable

Creation6 + Form6

Program IC + Pattern IC	Creation6 + Form6
03, 13	Incompatible
23, 33, 43, 53	Compatible